



ECS-2 Cut Sheet

Features

- Plug & Play



Overview

The ECS-2 cable set is designed to connect Hydro-X to most LED drivers with a pigtail wiring. The ECS-2 comes with a 16 ft RJ12 cable, a Y-splitter and a special 4 ft RJ12 / 3.5mm jack cable. The special cable connects to your lighting fixture / LED driver using the two-screw terminal block to connect to loose wires on the LED driver. Simply connect the two wires from your LED driver to the terminal block, each of the lights being controlled are wired in a “daisy-chain” configuration back to the Hydro-X LMA adapter.

M Product Specifications

*Dimensional
Diagram*

Package Content

- 1 x 16 ft RJ12 Cable
- 1 x 4 ft RJ12 to 3.5 Jack Cable
- 1 x T-shaped Splitter
- 1 x 3.5mm Female Barrel Connector

Input Voltage

12V

Maximum Current

0.2A

Working Environment

Temperature 32-122°F, Humidity<90%

Packaging Dimensions

156mm(L) x 83mm(W) x 30mm(H)

G.W. per pack

0.18kgs

